

# NADITBNC-FX

Female XLR cable end 110  $\Omega$  input - female BNC 75  $\Omega$  output. Interface balanced and coaxial lines.

## Features & Benefits

- Allow long cable runs for digital audio signals via low attenuation coax lines
- Match balanced to coaxial lines
- Match impedances 110  $\Omega$  to 75  $\Omega$
- Simple to use, passive units



## Technical Information [hide](#)

### Product

Title	NADITBNC-FX
-------	-------------

Connection Type	Adapter
-----------------	---------

Gender	female
--------	--------

### Electrical

Frequencyrange	0.1 - 6 MHz
----------------	-------------

Rated voltage	$\leq 5$ V p-p
---------------	----------------

VSWR	< 1.1
------	-------

Return loss	> 26.4 dB
-------------	-----------

Insertion Loss	< 0.3 dB @ 0.1 MHz to 10 MHz
----------------	------------------------------